

WARNING: DO NOT TOUCH TRIM POTS INSIDE PEDAL! YOU WILL NOT MAKE ANY ASPECT OF THE ECHO 600 BETTER!! THEY HAVE BEEN SET FOR OPTIMUM PERFORMANCE!!! DO NOT TOUCH!!!!

MALEKKO HEAVY INDUSTRY CORPORATION ™

OPERATING INSTRUCTION FOR ECHO 600 ANALOG DELAY PEDAL:

PLEASE READ THROUGH THIS USER'S MANUAL ONCE BEFORE GRABBING A SCREWDRIVER.

FIRSTLY: I KNOW I JUST SAID NOT TO MESS WITH THE TRIM POTS INSIDE THE PEDAL, BUT THERE IS ONE POT YOU WILL NEED TO ADJUST: THE GAIN POT. THIS IS BECAUSE WE DO NOT KNOW HOW YOU WILL USE THE ECHO 600, AND WE WANT IT TO BE FLEXIBLE ENOUGH FOR ANY USE. THEREFORE, YOU WILL NEED TO SET THE GAIN TRIM POT FOR YOUR SET-UP. THIS IS VERY SIMPLE: IF THE VOLUME DROPS WHEN YOU TURN ON THE ECHO 600, INCREASE THE GAIN TRIM POT. USING A SMALL PHILLIPS SCREWDRIVER (DO I NEED TO WRITE THIS?), TURN IT TO THE RIGHT. TRIAL AND ERROR WILL GET YOU THE DESIRED RESULT. SET THE "ECHO" KNOB ALL THE WAY DOWN—THIS WILL BE YOUR DRY LEVEL AND DRY SOUND ONLY. NO DELAY WILL BE HEARD. NOW SET THE GAIN. THE GAIN TRIM POT IS THE ONE WITH THE CIRCLE AROUND IT AND SAYS "GAIN".

WARNING: DO NOT TOUCH TRIM POTS INSIDE PEDAL! YOU WILL NOT MAKE ANY ASPECT OF THE ECHO 600 BETTER!! THEY HAVE BEEN SET FOR OPTIMUM PERFORMANCE!!! DO NOT TOUCH!!!!

\*THE T/B TOGGLE SWITCH ON THE SIDE BY THE OUTPUT JACK IS USED FOR CHOOSING BETWEEN TRUE BYPASS OUTPUT AND BUFFERED OUTPUT. (T=TRUE BYPASS, B=BUFFERED) THIS CHOICE WILL AFFECT THE GAIN OF THE PEDAL. PLEASE PLACE THE ECHO 600 IN YOUR RIG, PLAY AROUND WITH IT, AND DECIDE THE BEST ARRANGEMENT FOR YOUR SET-UP.

\*THE 0-600 KNOB IS DELAY TIME (0 TO 600ms)

\*THE ECHO KNOB BLENDS DELAY WITH YOUR DRY SIGNAL.

\*THE EXCESS KNOB SETS THE DELAY REGENERATION AMOUNT. (THIS AMOUNT CAN ALSO BE CONTROLLED BY USING AN EXPRESSION PEDAL)

\*THE W/D SWITCH ON THE TOP FRONT SELECTS WET OR DRY FOR THE SECOND OUTPUT.

\*THE WET/DRY OUTPUT IS A SECOND OUTPUT FOR YOU TO GET CRAZY WITH.

\*THE EXP IS AN EXPRESSION PEDAL INPUT WHICH CONTROLS THE EXCESS AMOUNT (REGEN)

OPERATE WITH 9V 200ma 2.1mm NEG TIP **REGULATED** (if not regulated, you could kill your new pedal) ADAPTER (not included)

The VisualSound 1SPOT power supply is NOT compatible with MALEKKO EKKO pedals. Use of this power supply will void manufacturer warranty.

WARNING: DO NOT TOUCH TRIM POTS INSIDE PEDAL! YOU WILL NOT MAKE ANY ASPECT OF THE ECHO 600 BETTER!! THEY HAVE BEEN SET FOR OPTIMUM PERFORMANCE!!! DO NOT TOUCH!!!!

WWW.MALEKKOHEAVYINDUSTRY.COM

FABRIQUÉ À LA MAIN AUX ETATS-UNIS HAND MADE IN USA

